



50HZ 3000 RPM



PR
PORTABLE RANGE

INVERTER PORTABLE GENERATOR GR2500

1 KEY FEATURES



Single phase



Gasoline



Grupel



50Hz




3000rpm

Continuous Power (PRP) (kW)	2.000
Starting Power (kW)	2.200
Frequency (Hz)	50
AC Voltage (V)	230
Automatic Voltage Regulator	Yes / Inverter
Fuel Tank Capacity (L)	4,5
Used fuel	Unleaded Petrol
Engine type	4 stroke
Starter system	Manual
Safety for lack of oil	Yes
Noise level (dBA) @ 7m	68

DIMENSIONS

(L) Length (mm)	500
(W) Width (mm)	285
(H) Height (mm)	455
Weight while empty (kg)	22



EXTRAS

Sockets	116 amp schuko socket	Frequency meter	Yes
Circuit Breaker	Yes	Auto Start	No
Hour Counter	Digital	ATS	No
Possibility of parallel	Yes	Command start	No
Battery	No	DC Output	Yes - 12vdc 8 amp
Voltmeter	Digital	USB	Yes - 1.0A + 2.1A

FRONT PANEL

